

**MCGINN & GIBB, PLLC**  
**A PROFESSIONAL LIMITED LIABILITY COMPANY**  
**PATENTS, TRADEMARKS, COPYRIGHTS, AND INTELLECTUAL PROPERTY LAW**  
**8321 OLD COURTHOUSE ROAD, SUITE 200**  
**VIENNA, VIRGINIA 22182-3817**  
**TELEPHONE (703) 761-4100**  
**FACSIMILE (703) 761-2375; (703) 761-2376**

**APPLICATION  
FOR  
UNITED STATES  
LETTERS PATENT**

**APPLICANT: Toshiyuki Tamura et al.**

**FOR: COMMUNICATION SYSTEM,  
COMMUNICATION METHOD AND  
SWITCHING NODE**

**DOCKET NO.: NEC-F108/USA**

05998316-070901

COMMUNICATION SYSTEM, COMMUNICATION METHOD  
AND SWITCHING NODE

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to an interface between a network for transmitting a bandwidth-compressed signal and a network for transmitting a signal which is not bandwidth-compressed. Particularly, in an interface between a switching node of a core network, which is connected to a communication network and use to decode the bandwidth-compressed audio signal transmitted through a radio access network and a switching node of the radio access network, which is connected to the communication to transmit a bandwidth-compressed audio signal, the present invention relates to an insertion control of a transcoder, which is provided in the switching node of the core network. Incidentally, the switching node of the radio access network is referred to a RNC (Radio Network Controller) and the switching node of the core network having the transcoder may be a MSC (Mobile Switching Center) or a MGS (Media Gateway Server), which has a gateway switching function. Since these switching nodes, that is, the MSC and the MGS, are the same in an insertion control operation of the transcoder except functional roles thereof in the core network, the MSC will be described as a typical example of the switching node of the core network, which includes the transcoder.

2. Description of the Related Art

A new mobile communication system has been proposed, which is constructed with a core network provided as a fixed network, for performing a position control, a call control and a service control and at least one radio access network for controlling and terminating a radio technology and has an interface between the RNC of the radio access network and the MSC of the core



shows the system in which the bandwidth-compressed audio signal is transmitted by converting it into the 64kbps PCM signal by using the transcoder TC.

Assuming that a receiving side is a radio terminal utilizing the same  
5 audio signal compression coding system as that used in a transmitting side, a CODEC is inserted into each of at least four locations in a route from a transmitting side to a receiving side. That is, a CODEC in a transmitting terminal, a transcoder of a switching node MSC on the transmitting side, a transcoder of a switching node MSC on the receiving side and a CODEC in the  
10 receiving terminal are necessary to code and decode the signal. Therefore, distortion of transmitting signal is accumulated due to the coding and decoding operations of these CODECs, resulting in a degraded audio signal quality. Further, if the transcoders are provided in all of channels of the switching node MSCs, the cost for installing the transcoders is increased and a signal delay  
15 occurs due to the signal conversions.

In a case where the same audio signal compression coding system is employed in the respective mobile communication networks, each of the transmitting and receiving terminals has to equip with a CODEC capable of performing the same processing. Therefore, there is no need of converting the  
20 audio signal into the 64kbps PCM signal by inserting the CODEC into each switching node MSC. It is clear that there is no problem if the audio signal is transmitted as a bandwidth-compressed, narrow band signal within the core network without using a transcoder. In such case, it is possible to reduce the cost of installation of the transcoders and to improve the quality of audio signal  
25 since the number of the coding and decoding steps is reduced. Therefore, in the mobile communication networks to which the same compression coding system can be applied, a system in which a bandwidth-compressed audio signal is transmitted as it is, without inserting transcoders into the switching nodes in

09609816-070001  
T00070-9166660

the core network. The latter system is referred to as Transcoder-Free-Operation (TrFO) system.

The Transcoder-Free-Operation system is shown in FIG. 10.

When a switching node MSC is controlling a communication between a  
5 transmitting terminal and a receiving terminal by by-passing a transcoder thereof according to the Transcoder-Free-Operation system, there may be a case where a tone signal in an audio frequency band is to be sent to either one or both of the transmitting terminal and the receiving terminal. For example, there is a case where a tone signal indicative of another call is to be inserted  
10 into the transmitting and receiving terminals. Further, when a transmitting terminal is of the prepaid system and a prepaid amount is substantially spent, it is necessary to insert a tone signal into the transmitting terminal.

A tone signal generator for generating such tone signal is provided in the switching node MSC in the core network and operates to insert the tone  
15 signal into at least one of the communicating terminals. The tone signal generated by the tone signal generator is a 64kbps PCM signal. Therefore, when the tone signal is inserted into the switching node RNC in which a bandwidth- compressed audio signal communication is performed, it is necessary to convert the 64kbps PCM audio signal into a bandwidth-  
20 compressed, a narrow band audio signal by a transcoder.

In such situation, when the switching node MSC of the core network inserts the transcoder into a call, which is performed through the Transcoder-Free-Operation connection, it is necessary to re-initialize the transcoder between the switching node MSC of the core network and the switching node  
25 RNC of the radio access network. This is because the switching node MSC of the core network does not recognize a parameter for the bandwidth compression coding in the call through the Transcoder-Free-Operation connection.

00000016.070001

The new mobile communication system, it has been proposed to use an AMR (Adaptive Multi Rate Codec) as the compression coding system. The AMR can dynamically determine the conversion rate in a range from 4.75kbps to 12.2kbps, for example. Further, a service class is assigned according to a tolerable error rate. The assignment of the coding frame of the AMR is performed by transmitting a RFCI (Rab sub-Flow Combination Identifier) information, which assigns Service Data Unit (SDU) size of a table describing conversion types between users, by using the user layer and performing a mutual negotiation between a transmitting terminal and a receiving terminal.

As mentioned, in the Transcoder-Free-Operation using the AMR coding system, the setting information of the compression coding is determined by the users by using the user layer of the user interface between the switching node MSC of the core network and the switching node RNC of the radio access network. Therefore, when the switching node MSC of the core network tries to insert the transcoder into a call under communication through the Transcoder-Free-Operation connection, the switching node MSC does not recognize its RFCI information as mentioned previously. Therefore, in order to insert the transcoder into the call under communication through the Transcoder-Free-Operation connection, it is necessary to execute the initializing procedure between the transcoder to be inserted and the switching node RNC of the radio access network. When the re-initializing procedure is executed during the communication, it is necessary to execute a plurality of sequences such as re-setting of a Radio Access Bearer between the switching node RNC and the switching node MSC and re-setting of a Radio Access Bearer between the terminal MS and the switching node RNC, etc. Therefore, if the insertion of the transcoder to the call through Transcoder-Free-Operation connection by performing the re-initializing procedures, there is a risk of such as delay of connection and instantaneous cut-off of sound, etc.

## SUMMARY OF THE INVENTION

An object of the present invention is to provide a communication system capable of inserting a transcoder into a call through the Transcoder-Free-Operation connection without requiring the re-initializing procedure.

5           Another object of the present invention is to provide a communication system and a method with which degradation of service, such as connection delay and/or instantaneous sound cut-off, does not occur even when a transcoder is inserted into a call through the Transcoder-Free-Operation connection.

As mentioned previously, the insertion of the transcoder into the call under communication through the Transcoder-Free-Operation connection in the switching node MSC of the core network requires the execution of the initializing procedure since the switching node MSC does not recognize the RFCI information of the AMR coding system, which is necessary in inserting the transcoder. Since the switching node RNC terminates the radio technology, it recognizes the RFCI information for the AMR coding. Therefore, in order to perform the insertion procedure of the transcoder easily without performing the re-initializing procedure, it is enough that the switching node MSC of the core network inquires of the switching node RNC of the radio access network about the RFCI information and sets the RFCI information from the switching node RNC in the transcoder. Since the RFCI information is determined by the user layer of the user interface Iu, it is enough to provide a protocol of the inquiry of the RFCI information to be made by the core network and an answer thereto from the switching node RNC of the radio access network in the user layer. By providing the inquiry protocol in the protocol of the user layer of the user interface Iu, it is possible to insert the transcoder without executing the re-initializing procedure.

Alternatively, it is possible to perform the inquiry from the switching

node MSC of the core network to the switching node RNC of the radio access network in not the user layer of the Iu interface but the control layer thereof.

That is, the present invention resides in a communication system comprising a first network including a switching node for transmitting a non-  
5 bandwidth compressed signal and a second network including a switching node for transmitting a bandwidth compressed signal. The switching node of the first network includes a transcoder for performing a conversion between the bandwidth-compressed signal and the non-bandwidth-compressed signal and is operable in either a first mode for transmitting the non-bandwidth-compressed  
10 signal by inserting the transcoder to perform a conversion between the bandwidth-compressed signal and the non-bandwidth-compressed signal or a second mode for transmitting the bandwidth-compressed signal by by-passing the transcoder. The switching node of the first network includes means for inserting the transcoder in the second mode by inquiring of the switching node  
15 of the second network about a setting information of the transcoder and setting the transcoder on the basis of a response from the switching node of the second network.

Further, the present invention resides in a communication system comprising a radio access network including a switching node for transmitting  
20 an audio signal as a bandwidth compressed signal and a core network including at least one switching node for transmitting an audio signal as a bandwidth compressed signal. The switching node of the core network includes a transcoder for performing a conversion between the bandwidth-compressed signal and the non-bandwidth-compressed signal and is operable in a  
25 Transcoder-Free-Operation connection mode for transmitting and receiving the bandwidth-compressed signal between a calling terminal and a called terminal mutually without using the transcoder according to a negotiation between the calling terminal and the called terminal. The switching node of the core





radio access network about a setting information of the transcoder for the Transcoder-Free-Operation connection, sets the transcoder on the basis of the setting information from the switching node of the radio access network and inserts the transcoder.

5           The inquiry may be performed by using a user layer of an Iu interface defined as an interface of the switching node of the core network and the switching node of the radio access network and the setting information of the transcoder may be a RFCI information of an AMR (Adaptive Multi Rate Coding) system.

10           Further, the present invention resides in a switching node operable in either a first mode in which a transcoder is inserted to perform a conversion between a signal bandwidth compressed and a signal not bandwidth compressed or a second mode in which a bandwidth-compressed signal is transmitted by by-passing the transcoder. The switching node comprises means  
15           for, in the second mode, inquiring of another switching node about a setting information of the transcoder and inserting the transcoder on the basis of the setting information from the another switching node.

            This switching node is a switching node opposing to a switching node of a radio access network in which an audio signal is transmitted as a bandwidth  
20           compressed signal and the setting information may be a RFCI in an Adaptive Multi Rate Coding system.

#### BRIEF DESCRIPTION OF THE DRAWINGS

Preferred embodiments of the present invention will be described with reference to the accompanying drawings, in which:

25           FIG. 1 is a conceptual figure showing a protocol of Iu interface according to the present invention;

            FIG. 2 illustrates an inquiry operation of RFCI information in a first embodiment of the present invention;

FIG. 3 illustrates an insertion of a trunk for three-talker situation in the first embodiment of the present invention;

FIG. 4 is a flowchart for inserting the three-talker trunk in the first embodiment of the present invention;

5        FIG. 5 illustrates a tone inserting operation to be performed at a time when a prepaid amount is almost spent in a second embodiment of the present invention;

FIG. 6 is a flowchart showing the tone inserting operation when the prepaid amount is spent in the second embodiment of the present invention;

10       FIG. 7 illustrates a tone inserting operation when a prepaid amount is spent in a conventional system;

FIG. 8 shows a system construction of a mobile communication system to which the present invention is applied;

15       FIG. 9 shows a construction of the present system in a transcoder connection mode; and

FIG. 10 shows a construction of the present invention in a transcoder-free-operation connection mode.

#### DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

20       FIG. 1 shows a concept of a communication system of the present invention. In FIG. 1, the communication system includes a core network having a switching node MSC 100 and a radio access network having a switching node RNC 200. The switching node MSC 100 of the core network and the switching node RNC 200 of the radio access network transmit and receive an AMR frame each other according to a protocol of a user layer of a user interface Iu. A  
25       transcoder TC 101 is included in the switching node MSC 100. The transcoder TC 101 functions to convert an audio signal from the radio access network, which is bandwidth-compressed according to the AMR coding, into a 64kbps PCM signal and to convert a 64kbps PCM signal from the core network into the

AMR coded signal. A Diversity Handover Trunk (DHT) 201 of the switching node RNC of the radio access network takes its share of a handover function in a diversity operation mainly.

The user interface Iu uses AAL2 (ATM Adaptation Layer type 2) in  
5 ATM (Asynchronous Transfer Mode) and an inquiry of RFCI parameter of AMR  
code is performed by using a layer defined as a user layer of the Iu interface.

### First Embodiment

An example in which a communication is changed from a call through the transcoder-free-operation connection to a communication between three 10 talkers by inserting a transcoder will be described with reference to FIGs. 2 to 4.

For example, during a communication between two talkers through the transcoder-free-operation connection, a communication path is formed by bypassing the transcoder TC of the switching node MSC 100. In such case, when it is desired to introduce the third party using a 64kbps PCM signal into the communication to realize a communication between three talkers, it is necessary to insert transcoders into the two terminals, which are using the AMR coded audio signal, respectively, to connect them to one terminal of a three-talker communication trunk 104 and to connect the other terminal of the trunk 104 to a trunk on the side of the third talker.

An example of this operation will be described with reference to a flowchart shown in FIG. 4. It is assumed that talkers A and B are communicating with each other through the transcoder-free-operation. It is further assumed that, in such state, there is a call from a talker C using a fixed telephone to join the communication between the talkers A and B.

When there is a request call of three-talker communication from the third talker C, a three-talker communication trunk 104 is caught in the switching node MSC and one terminal of the trunk 104 is connected to a trunk

of a communication path to the C and simultaneously two transcoders for the A and B are caught. When the two transcoders for the A and B are caught, an inquiry of the switching nodes RNC 200 of the radio access networks, to which the A and B belong, about RFCI information used in the connection call between the A and B is performed in the user layer of the Iu interface. Although the switching node MSC 100, which is being switched to the three-talker communication, does not recognize the RFCI information currently in use, the switching node NSC 200 recognizes the RFCI information currently used in the radio access network. In response to the inquiry, the switching node RNC sends a value of the RFCI parameter to the switching node MSC. The switching node MSC 100 sets the transcoders on the basis of the RFCI thus acquired and connect the two transcoders to the three-talker communication trunk 104. Thus, the three-talker communication using the 64kbps PCM signal is realized.

In FIGs. 3 and 4, the switching node MSC of the core network inquires of one of the switching nodes RNC to which the respective A and B belong, about the RFCI information. However, the switching node MSC 100 may inquire of both the switching nodes RNC about the RFCI information. Incidentally, the switching node MSC 100 and the switching node RNC 200 can transmit/receive the RFCI information by means of only the user layer protocol of the Iu interface.

In a case where there is a call from a third party during the transcoder-free-operation connection between two talkers and a tone signal indicative of the call is sent to the talkers, one terminal of the three-talker communication trunk 104 is connected to a 64kbps PCM tone signal generator and the other terminal of the trunk is connected to the talkers by inserting the transcoders, similarly to the procedure for realizing the three-talker communication.



the same as those of the present invention. Thereafter, the re-setting procedure of the Radio Access Bearer (RAB) between the switching node MSC 100 and the switching node RNC 200 is performed in the conventional system (p3'). Further, a re-setting procedure of a radio bearer on the Radio Resource Control (RRC) protocol between a terminal MS and the switching node RNC is performed (p4'). This procedure p4' is ganged with the procedure p3'. Upon the re-set RAB, a bearer change of the AAL2 link of the ATM corresponding thereto is performed (p5'). With the bearer established, the initializing processing in the user layer of the Iu interface is performed (p6') and the transcoder 102 connected to the remote side switching node RNC is re-set (p7'). The procedure p7' is activated in parallel to the procedures p3' to p6'. Finally, the prepaid system subscriber can hear the tone by connecting the tone generator 105 to the transcoder 101.

Comparing the present communication with the procedures performed in the conventional system shown in FIG. 7, it is possible according to the present invention to insert the transcoder into the call of the transcoder-free-operation connection without necessity of the re-setting of the bearer between the switching node MSC and the switching node RNC, the re-setting of the bearer between the MS and the switching node RNC, the initializing processing between the local side switching node RNC and the switching node MSC and the initializing processing between the remote side switching node RNC and the switching node MSC.

Although, in the second embodiment, the inquiry of the RFCI information is performed in the user layer of the Iu interface protocol, it is possible to perform the same by using the control layer thereof, that is, the Radio Access Network Application Part (RANAP).

As described hereinbefore, according to the present invention, it is possible to insert a transcoder into a call of transcoder-free-operation connection without using the re-initializing processing. Therefore, it is possible

to prevent occurrence of the problems such as delay of connection and instantaneous cut-off of sound, etc., due to the re-setting processing of the bearer between the switching nodes and the re-setting processing between the MS and the switching node, which are performed during a communication to  
5 re-initialize the system.

Further, according to the present invention, the procedure for insertion of the transcoder is simplified and the number of messages to be used can be reduced. Therefore, the processing therefor can be simplified.

09899816-070901  
T06070-9186880